

# SEW Eurodrive MOVITRAC

SEW Eurodrive series, model MOVITRAC-07 inverter, MovitracB

<http://sg.sew-eurodrive.com/>

## HMI Setting:

Parameters	Recommend	Option	Notes
PLC type	SEW Eurodrive MOVITRAC		
Com port	RS-485		
PLC Station No.	0	0~255	
Baud rate	9600		
Data bit	8		
Parity bit	Even		
Stop bit	1		

## Device address:

Bit/Word	Device Type	Format	Range	Memo
W	INDEX	DDDdddd	DDD(000~255) dddd(08000~25000)	D: Sub Index d: Index
B	INDEX_Bit	DDDdddd(h)	DDD(000~255) dddd(08000~25000) h(0~f)	D: Sub Index d: Index h: Index_bit

- The MOVITRAC-07 doesn't support Sub index ( other series maybe support ) , please fixed to input 000.
- When input D and d, the correct format example as follow : Sub index 15, Index 8359, Format is 01508359

## Wiring diagram:

EasyView MT8000  
RS-485 2W (COM 1)

MOVITRAC-07  
RS-485

