


1 Installation and Startup Guide

This document covers the installation of cMT2158X Series HMI, for the detailed specifications and operation, please refer to Datasheet, Brochure and EasyBuilder Pro User Manual. Please read all warnings, precautions, and instructions on the device carefully before use.

Install Environment:

NEMA Rating	The HMI product is NEMA 4 rated (Indoor Only).
Electrical Environment	The HMI product has been tested to conform to European CE requirements. This means that the circuitry is designed to resist the effects of electrical noise. This does not guarantee noise immunity in severe cases. Proper wire routing and grounding will insure proper operation.
Environmental Considerations	<ol style="list-style-type: none"> (1) Make sure that the displays are installed correctly and that the operating limits are followed. Avoid installing units in environments where severe mechanical vibration or shocks are present. (2) Do not operate the unit in areas subject to explosion hazards due to flammable gases, vapors or dusts. (3) Do not install the unit where acid gas, such as SO₂ exists. (4) This device should be mounted in the vertical position and for use on the flat surface enclosure. (5) For use in Pollution Degree 2 Environment and dry location. (6) Relative Humidity: 10% ~ 90% (non-condensing)
Cleaning Considerations	Clean the device using dry cloths. Do not use liquid or spray detergents for cleaning.
IP Rating	IP 66
 Warning	Protection impairment if used in a manner not specified by the manufacturer. Déficit de protection si utilisé d'une manière non spécifiée par le fabricant.

2 Unpacking the Unit

Unpack and check the delivery. If damage is found, please contact the supplier.

NOTE: Place the operator panel on a stable surface during installation. Dropping it or letting it fall may cause damage.


The package includes:

- (1) Installation Instruction, 2-sided A4 *1
- (2) Human Machine Interface *1
- (3) Power Connector *1
- (4) Brackets & Screws *1 pack
- (5) Fuse 1.6A/250V 5*20mm *1

3 Installation Instructions

Use a control box that provides enough space for the HMI operator panel in position, using all the provided brackets and screws. The weight of the panel is 2.6 ~ 3.9 lbf.in. (For reaching waterproofing, preventing the panel from being deformed, Plan for adequate space around the unit enclosure, for ventilation and cables. Clearance from other devices inside the enclosure. The temperature around the unit must be 0 ~ 40°C. Minimum required clearances (along the enclosure):
 Bottom / Sides 15 mm
 Maximum panel thickness: 4.5 mm

4 Power Connections

 Power Connector Specifications:
 Wire AWG: 24~12
 Wiring Conductor Minimum Temperature: 0 ~ 40°C
 Screw Torque: 4.5 lbf-in (max.)
 Copper conduct only.

NOTE:

1. Connect positive DC line to the '+' terminal.
2. When downloading project using EasyBuilder Pro with PLC and PC simultaneously, the result in damage to HMI or PC.

5 System Settings

When the HMI powers up and displays the login screen, open the Setting page. To configure the system, or later, tap "configure", and a login window will appear. Enter the system password (default: 111111). If the password is correct, and log in to make changes. In the Settings page, set HMI Time/Date/Name, and other settings.

6 EasyBuilder Pro Software

Launch EasyBuilder Pro software, select the connection dialog box: Select Ethernet > IP tab > select the IP address file to HMI.

Using screensaver and backlight save the settings by displaying the same image on HMI. (Please refer to EasyBuilder Pro User Manual for details.)

7 Communication Connections

NOTE:

1. Only Tx & Rx (no RTS/CTS) may be used for COM1 RS-232 when COM3 RS-232 is also used.
2. COM1 and COM3 RS-485 2W support MPI 187.5K, please use one at a time.
3. COM1 RS-485 / COM3 RS-485 with isolation protection.

1 2 3 4 5 6 7 8 9 Con.B

COM1/COM3 [RS232] 9 Pin, Male, D-sub

PIN#	COM1 [RS232]4W	COM3 [RS232]2W
1		
2	RxD	
3	TxD	
4		
5	GND	
6		
7	RTS	TxD
8	CTS	RxD
9	GND	

5 4 3 2 1 9 8 7 6 Con.A

COM1/COM3 [RS485] 9 Pin, Female, D-sub

PIN#	COM1 [RS485]2W	COM1 [RS485]4W	COM3 [RS485]2W
1	Data-	Rx-	
2	Data+	Rx+	
3		Tx-	
4		Tx+	
5	GND (isolation)		
6			Data-
7			
8			
9			Data+

8 Restore Factory Default

There are two methods to restore factory default, both of which will erase all project files and data stored on the device.

1. Follow the instructions in section 5 of this manual to open the Setting page and select the appropriate page based on the OS version before pressing "Reset HMI to default":
For OS versions 20231201 or later, select the "System Properties" page, press "Reset HMI to Default," and select "Reset".
For OS versions before 20231201, select the "Reset Options" page, press "Reset HMI to default", and enter "yes".
2. Alternatively, during login, enter "default111111".
For OS versions 20231201 or later, select "Reset".
For OS versions before 20231201, enter "yes".

9 Battery Replacement

Battery replacement shall be performed by qualified personnel only and care must be taken when handling lithium batteries. For more information on battery replacement and disposal considerations, please refer to the following link:

http://www.weintek.com/download/MT8000/eng/FAQ/FAQ_103_Replace_Battery_en.pdf


CAUTION



Power

NOTE: Make installing the u

Use power output powered by DC p systems. The pow supply. The peak s




Fusing Require-
ments

Fuse min. rating: 1 within 5 seconds o of the DC power is Replacing fuse sha <http://www.weintek.com>




High Voltage

An Internal fuse w voltage sources sh



Emergency Stop

A Hard-wired EME ICS Safety Recom



Supply Voltage
Condition


Do not power the power supply. Note power the unit.



Wire Routing


- a. Power wire ler
- b. Please use tw impedance ma
- c. If wiring is to b devices.
- d. Keep AC, high
- e. Add a resistor supply and the dissipation. Ty

DANGER



Hardware
Considerations

The system desig thereby create an interface can lea physical injury to If you use any pr potential safety ha steps depend on installation of Cont installation of Cont



Programming
Considerations

To conform to ICS ensure that all wr checks built into the personnel.

Limited Warranty

This product is limited warranted ag The proven defective product will e This warranty shall not cover any p
(a) Out of warranty period which is 12 month
(b) Damage caused by Force Majeure, accid
(c) Product has been repaired or taken apar
(d) Products whose identification markings h